

YF-8070



CAT II
600V

600A AC Clamp On Meter

DISPLAY

- 3½ digits LCD with maximum reading 2000.
- Low battery indication: " ".

FUNCTIONS

- Function keys: Data Hold, Peak Hold.
- Test ranges: ACV, ACA, Ω, Hz, Continuity.
- Non-contact frequency measurement.

YF-8050



CAT III
1000V

1000A AC Clamp On Meter

DISPLAY

- 3¾ digits LCD with maximum reading 4000.
- Overload indication: "OL".
- Low battery indication: " ".

FUNCTIONS

- Auto power off.
- Function keys: Peak Hold.
- Test ranges: ACV, ACA, Ω, Frequency, Continuity.
- Non-contact frequency measurement.

Specifications

YF-8070	YF-8050	Model
600A	1000A	Max measuring current
2000	4000	Display counts
35mm	52mm	Max. Conductor size
10mA-600A ±(2.0%+5)	1mA-1000A ±(1.5%+4)	AC Current
0.1V-750V ±(1.2%+3)	0.1V-750V ±(1.0%+4)	Leakage current
1Ω-2000Ω ±(1.0%+2)	1Ω-4000Ω ±(1.0%+2)	AC Voltage
YES	YES	Resistance
1HZ-5MHZ ±(0.8%+3)	1Hz-4000KHz ±(0.8%+3)	Continuity buzzer
YES	YES	Frequency
YES	YES	Bargraph
221*62*35mm	250*70*35mm	Peak hold
330g	420g	Data hold
		Size
		Weight